

PL140

Public Address - Attenuators

Attenuator module with 40W transformer for 100V line with message priority. With it, 6 output levels can be selected by means of a 12-position rotating selector switch, with a zero between every two levels.

GENERAL FEATURES

- Attenuator with transformer for 100V line.
- 6 attenuation positions, with a zero between every two levels.
- 12-position rotating selector switch.
- Message receipt even when on level 0.
- Bridge to select message mode.
- Control Terminal to control the message receipt by external relay (See application diagram).

TECHNICAL CHARACTERISTICS

Inputs:	Línea 100V
Output Impedance:	250 Ohm
V Output Adjusted Between:	100V, 50V, 25V, 12.5V, 6.25, 3.125
Nominal Input Level for Warning Switching:	Línea 100V
Dimensions:	dos módulos de 45 x 45mm
Weight:	250grs

INSTALLATION

Before making the connection make sure the amplifiers of the system
are switched off. Make the connection according to the following instructions:

TERMINALS:
IN+ - + Input, 100V line
IN- - - Input, 100V line
CTR - Input for message control by external relay
OUT+ + Output for 100V line speaker (Max.power 40W)
OUT- - Output for 100V line speaker (Max.power 40W)

These features given for information only. Sonelco.com reserve the right to make changes without notice in order to improve the product. More information: (+34) 976 259 135 / (+34) 609 719 454 / sat@sonelco.com