



PCP1222

Background Music - Controls and Modules (45x45mm)

3+3 W stereophonic amplified controller with digital volume adjustment, 2 channels selector. Loudness, Superbass, Scan, Sleep functions, output for earphones and jack input for external source

GENERAL FEATURES

- Electronic ON/OFF switch.
- Luminous ON indicator LED type.
- Key pressed luminous indication (Vol+, Vol-).
- 3+3W stereophonic amplifier with outlet for standard 4 Ohm speakers.
- Integrated audio processor.
- Microprocessor-controlled progressive Loudness and Superbass.
- SCAN function, (remote change of radio station in a SONECO tuner).
- Output for stereo earphones, with disconnection of speakers.
- Input for outside audio signal (Aux) for amplification through speakers, with automatic disconnection of line signal.

TECHNICAL CHARACTERISTICS

Music channels:	2
Power:	1.5 + 1.5 W RMS (8 Ohm)
Output Impedance:	4 Ohm
Maximum Power:	3 + 3 W RMS (4 Ohm)
Maximum Current	Terminal 3: 2 A
Frequency Response:	4 Ohm 119 Hz - 25KHz. (-3dB) / 8 Ohm 75 Hz - 25KHz
Signal/Noise Ratio:	> 90dB
Crosstalk:	-70 dB
Sensitivity:	1.6 V
Aux Input:	500 mV
Mains Input:	16 V DC
Maximum Consumption:	760 mA (4 Ohm) / 430 mA (8 Ohm)
Standby Consumption:	9 mA
Dimensions:	45x45x45 mm
Weight:	46 gr
Colours:	PCP1222-01 (White), PCP1222-02 (Anthracite grey), PCP1222-10 (Ivory), PCP1222-12 (Silver)

INSTALLATION

Universal box.

A front plate with support is required. See accessories.