



## PCB1245

Background Music - Controls and Modules (45x45mm)

Mono amplifier control 1W, with digital volume control (1 and 2). 4 mono music channel selector (6) and warning reception. Electronic on / off button (4). Adjustment of warning reception level by use of Vol+ (1) and Vol- (2).

### GENERAL FEATURES

- Electronic ON / OFF switch (4).
- LED type operation indicator light (5).
- Digital volume control (1 y 2).
- 4 music channel electronic switching "ch"(6).
- Channel number light indicator (3).
- Memory of last channel selected.
- 1.5W. mono amplifier with standard 8-Ohm loudspeaker outlet.
- Warning reception, even when the control device is switched off.
- The volume reception can be adjusted by using the Vol+/- buttons.
- Warning reception level memory.
- Voltage control by means of audio line.

### TECHNICAL CHARACTERISTICS

<b>Music channels:</b>	4
<b>Output Impedance:</b>	8 Ohm.
<b>Maximum Power:</b>	2 W RMS
<b>Maximum Current</b>	Terminal 3: 1 A
<b>Frequency Response:</b>	80 Hz. - 20 KHz. (-3dB)
<b>Signal/Noise Ratio:</b>	> 62 dB
<b>Crosstalk:</b>	-55 dB
<b>Mains Input:</b>	16 V DC
<b>Nominal Input Level for Warning Switching:</b>	15 V
<b>Maximum Consumption:</b>	230 mA
<b>Standby Consumption:</b>	9 mA
<b>Dimensions:</b>	45x45x26,5 mm.
<b>Weight:</b>	29 gr.
<b>Colours:</b>	PCB 1245-01 (White), PCB1245-02 (Graphite), PCB1245-10 (Ivory coloured)PCB1245-12 (Steel coloured)

### INSTALLATION

Universal box.

Need a decorative frame. See accessories.

